



CONTRACTOR GRADE

MX6 -1RM 6 Channel Mic/Line Mixer



- 6-channel mic/line mixer in a single rack space (1U)
- Balanced XLR mic and 1/4" TRS Line inputs—each channel
- Master volume and bass, treble controls
- Phantom power (15V) on channels 4-6 mic inputs
- Dual (low and high level) outputs
- Internal shielded power supply, ~115V/60Hz AC powered

The Avlex MX6-1RM is a 6-channel mic/line mixer in a single rack space designed for professional sound engineers and working musicians.

The MX6-1RM features balanced XLR mic and 1/4" TRS line inputs on each Channel, master volume, bass and treble controls, phantom power (15V) on channels 4, 5 & 6 mic inputs, balanced and unbalanced outputs, an Internal shielded power supply and all steel construction with rack ears.

The MX6-1RM is compact and versatile. It is ideal for small PA installations, keyboard mixing and many other applications.

MW6-1RM Specifications:

| | |
|--------------------|--|
| Input Channels | 6, mono balanced mic XLR / unbalanced line 1/4" TRS |
| Output Channels | Balanced XLR or 1/4" unbalanced phone; High or low output selectable Impedance: 600 ohms |
| Frequency Response | 10 Hz to 20 KHz, +/- 3 dB @ 0 dBm |
| THD | 0.1%, 20Hz - 20KHz @ 1KHz, 0dBm |
| Signal/Noise | >60dB |
| Master EQ | High & low, +/- 12 dB Low shelved: 100Hz High shelved: 10KHz |
| LED Indicator | Power on |
| Phantom Power | 15 Volts; channels 4,5 & 6 |
| Fuse | T250mA, 5 x 20mm glass type |
| Dimensions | 19" L-R x 8" F-B x 1.75" T- B |
| Weight | 7 pounds |