



**ACT-8T Digital Bodypack Transmitter**

These revolutionary encrypted digital wireless systems feature a 128-bit encryption key for maximum security against unauthorized listening, 24-bit audio quality, true digital RF transmission, SmartEQ™ microphone modeling and are PC-controllable.

**ACT-8T Features**

- Extremely rugged and miniature in design with magnesium alloy housing.
- Precision SMA antenna connectors with removable soft antennas. Robust mini-XLR connector.
- Bright LCD displays working channel, transmitter battery status, input levels and error code.
- User-friendly adjustable menu buttons.
- Ultra-compact size with adjustable belt clip can be worn comfortably right side up or upside down.
- Detachable Li-polymer battery pack can be recharged alone or together with transmitter. Battery delivers eight to ten continuous hours of operation from a 4-hour charge.
- World's first ACT function, allowing rapid and precise transmitter frequency set-up.

**Specifications**

Dimensions	60(W) × 84(H) × 24(D) mm / 2.4(W) x 3.3(H) x 0.9(D) "
Weight	135g / 4.8oz
Connector	Mini-XLR
Antenna	Detachable
RF Power Output	≤ 50mW (Country Dependant)
Spurious Radiation	≤ -60dBc
Frequency Generation	Phase-Locked Loop (PLL)
Frequency Stability	≤ ±0.005% at 0~50°C
Modulation Type	Digital Modulation
Audio Compression	Combiner DSP Technology
Battery Type	1200mA/h Rechargeable Lithium-Polymer
Battery Life	≥ 10 Continuous Hours